

ARCHITECTURAL LIGHTING - ARQ SYSTEM

ARQ MASTER Surface // ARQ MASTER Back

Main control of ARQ system

With only a previous ARQ Master programming and assigning it to the different lightings by means of the elements of the system (preset), each zone of the installation can be controlled by a pushbutton.

Programming of the system can be modified anytime in function of the needs. Therefore, this allows you to have a pre-programmed lighting system which can be quickly and simply activated.

Control and programming panel with display which can control up to 128 channels and define up to 128 presets with the mentioned channels and with

fade times.

Blackout pushbutton included.

Interface with the other network elements by CAN bus.

Maximum number of Arq Master in a network: 1.

DMX output to the dimmers for power control.

This product is available in two versions: surface or prepared to be hang on a wall.

Panels can be painted in different colours.



References: 03200120
03200121

Weight 0.8 Kg. // 1.45 Kg.

Dimensions 250x160x50 mm // 250x160x60 mm

Exterior finish Grey colour (other options)

Power supply 12V 1Amp. (DC)

Other characteristics:

Connection Internal terminals

Communication protocol CAN

Output signal DMX-512(1990)

Signal connector XLR 5 pins