

FIX MOTOR CONTROL

MOTOR DIGI RACK 6-1CV // MOTOR DIGI RACK 6-2CV

For controlling up to 6 motors of 1HP // 2HP

If it is required a centralized version that must include in a rack not only protections but signal and control too, with only one three-phase power hose to each one of the motors, Motor Digi Rack 6-1 and 6-2 are the best option. They are 4-unit rack 19" which can control independently up to 6 motors of 1HP or 2HP (depending on the model).

6 display groups to visualize motor group addresses. 6 rotating switch for selecting the address of each motor.

Three-phase 380V 50Hz power supply and power outputs to the motors by terminals on rear side.

For security reasons, there are safety switches which are connected in the rear side of the motor through terminals.

Motor protection by circuit breakers for each motor.

Differential current tripping device of 4 poles with a tripping current of 30mA.

Strong Stage recommends using these products to control Prolift motors.

Motors are controlled by MOTR DIGI 1, 6, 12 or 24.



References: 03000107
03000110

Weight	15 Kg.
Dimensions	482x176x360 mm
Exterior finish	Black colour
Power supply	Three-phase 380V 50Hz
Outputs	Up to 6 motors of 1HP // 2HP

Other characteristics:

- Maximum power 6x1HP // 6x2HP
- Emergency circuit Free-contact
- Positioned circuit Free-contact
- Type of connection Guide terminals
- Protection Three-phase differential 30mA
- Control signal RS-485
- Signal connector XLR-7pins
- Power supply connector 16 Amp. Cetac (male)



Address: C/ Potosí 40 08030 Barcelona Spain
Tel. (0034) 93 360 02 30 Fax. (0034) 93 274 47 47 Email: strong@strong.es