

ARCHITECTURAL LIGHTING - ARQ SYSTEM

ARQ FADERS Surface // ARQ FADERS Back

8-potentiometer panel control for ARQ system

ARQ Faders is a remote control that activates different presets, which have been previously programmed in the ARQ Master, by means of a pushbutton.

It is designed to have quick access to a pre-programmed lighting.

ARQ Fader is similar to ARQ Key, but it has 8-potentiometer to control and regulate directly DMX channels. Moreover, ARQ Fader can record up to 8 presets.

Control panel with 8-potentiometer channels and

one master. It includes potentiometers for adjusting the input and output times of the presets and 8 pushbuttons for launching and cancelling the previously recorded presets. There is a blackout pushbutton included.

Interface with other network elements by CAN bus.

Maximum number of ARQ Faders in a network: 4.

This product is available in two versions: surface or prepared to be hang on a wall.

Panels can be painted in different colours.



References: 03200138
03200141

<i>Weight</i>	0.8 Kg. // 1.4 Kg.
<i>Dimensions</i>	250x160x50 mm // 250x160x60 mm
<i>Exterior finish</i>	Grey colour (other options)
<i>Power supply</i>	12V 1Amp. (DC)

Other characteristics:

Connection Internal terminals

Communication protocol CAN

Output signal DMX-512(1990)

Signal connector XLR 5 pins

Addressing Mini Dips (unit-decimal)