

ARCHITECTURAL LIGHTING - ALBA SYSTEM

ALBA 1-2 ON/OFF

1-channel 2-kW dimmer (on-off)

ALBA series is composed of dimmers which are created to satisfy light requirements in small spaces where hall lights must be adapted to different kind of lightings.

This range is designed to control resistive and inductive lightings altogether.

ALBA is completed with Demux 6A which allow you to control different Alba series dimmers via DMX-512.

Possibility to be controlled with the following ways:

- Locally by a pushbutton
- Remotely by external pushbuttons
- Remotely by 0-10 V DC though Demux 6 A

It is prepared to be fixed on DIN 35 rail.



Reference: 24000058

<i>Weight</i>	0.4 Kg.
<i>Dimensions</i>	158x86x58
<i>Exterior finish</i>	White colour
<i>Power supply</i>	Single-phase 230V 50Hz

Other characteristics:

- Maximum output 2KW
- Protection Fuse 10 Amp. T
- Power supply conductor section 2,5mm²
- Connection through terminals