

# CONTROL - DMX ACCESSORIES

## SPLITTER 1/8 // SPLITTER 1/4

### 1-in 8-out splitter // 1-in 4-out splitter

Splitter for DMX-512 signal with one input and eight outputs (1/8 model) or four outputs (1/4 model).

Output signals are optoisolated. Input and outputs are protected against overvoltage too.

There are leds to confirm input signal, output

signals and mains.

Splitter1/8 is available in 1-unit rack-19" version (RACK) or the EMBEDDED model (for Wall dimmers). Splitter 1/4 is manufactured in a Box model or the EMBEDDED one (to be inserted in a Wall dimmer).



References: 03000028

03000031

<i>Weight</i>	3.5 Kg. (1/8 models)
	2.15 Kg. (1/4 models)
<i>Dimensions</i>	482x165x44 mm (RACK model)
	128x218x80 mm (BOX model)
	482x130x60 mm (EMBEDDED model)
<i>Exterior finish</i>	Black colour
<i>Power supply</i>	Single-phase 230V 50Hz



References: 03000081

03000083

<i>Other characteristics</i>
Power absorbed 10W
Safety fuse 5x20 1A.
Digital input/output signal DMX-512 (1990)
Digital input/output connector XLR-5 pins



Address:

C/ Potosí 40 08030 Barcelona Spain  
Tel. (0034) 93 360 02 30 Fax. (0034) 93 274 47 47 Email: strong@strong.es