

ARCHITECTURAL LIGHTING - ARQ SYSTEM

ARQ 8 KEYS / ARQ 4 KEYS / ARQ 2 KEYS (modelos Surface y Back)

8, 4 or 2-pushbutton panel control for ARQ system

ARQ Keys are remote controls that activate different presets, which have been previously programmed in the ARQ Master, by means of a pushbutton.

They are designed to have quick access to a pre-programmed lighting.

Control panel with 8, 4 or 2 (depending on the model) pushbuttons for Arq system. It is possible to

launch or cancel respectively 8, 4 or 2 presets, which are previously recorded.

Blackout pushbutton included.

Interface with other network elements by CAN bus.

Maximum number of ARQ Keys, no matter the type, in a network: 32, including Arq Faders.



Surface references: 03200108
03200104
03200102

Back references: 03200109
03200105
03200103

Weight 0,35 Kg. (surface model)

0,65 Kg. (back model)

Dimensions 160x98x50 mm (surface model)

160x98x60 mm (back model)

Exterior finish Grey colour (other options)

Power supply 12V 1Amp. (DC)

Other characteristics:

Connection Internal terminals

Communication protocol CAN

Output signal DMX-512(1990)

Signal connector XLR 5 pins

Addressing Mini Dips (unit-decimal)